Updating NCSP3, NCSP35, & NCSP3DCCT

- 1) Go to https://in-command.net/
- 2) Click on Control Systems at the top of the page, select iN•Command w/ **Global Connect**.
- 3) Scroll down until you see **Resources**. Click on **Software Updates**. Click on **Display Commander OS** & **Body Control Module**. Download both files one at a time, **do not** place the files within folders, and **do not** unzip the zipped file. Move the downloads to a USB flash drive please use drives **16GB or smaller**.
- 4) Insert the USB flash drive into the bottom of your iN•Command display. 5) On the iN•Command display, tap **Settings**.
- 6) Tap the Down Arrow and tap Software.
- 7) You should see the **DC** & **BCM Version**. One at a time tap each one, and tap **Update**.

DC Version file will explicitly be NCSP3-DC V2.5.66.zip
BCM Version file will explicitly be ncspbcmv1.04.75.bin
When downloading a file multiple times you may see a file renamed as ncspbcmv1.04.75
(1).bin

The (1) will not allow iN•Command to read the file

Note that the App version will be updated with the DC Version when applying DC OS update.

Current DC Version: 2.5.66 Current BCM Version: 1.04.75

